

TFD Array Feed System Losses

Typinski, 3/28/15

Feed line loss sweeps performed 28 Mar 2015				Device sweeps performed 11 Aug 2013				Loss Between Element Feed Points and Hybrid Outputs (dB)
Rack panel to gray point of entry box	Gray box to center J-box	Center J-box to outer J-box	Outer J-box to element balun	Synergy DQK-701B 90° Hybrid (one)	Mini-Circuits ZSC-2-1W+ Combiners (two)	AJ4CO BALUN16-1A 16:1 Balun (one)		
Freq (MHz)	One Way Loss (dB)	One Way Loss (dB)	One Way Loss (dB)	One Way Loss (dB)	Loss (dB)	Loss (dB)	Loss (dB)	
16	-0.99	-0.94	-0.75	-0.33	-0.21	-0.40	-0.52	-4.13
18	-1.04	-0.99	-0.79	-0.35	-0.26	-0.41	-0.54	-4.38
20	-1.09	-1.03	-0.84	-0.37	-0.29	-0.42	-0.55	-4.61
22	-1.15	-1.07	-0.89	-0.39	-0.32	-0.43	-0.57	-4.82
24	-1.20	-1.11	-0.93	-0.40	-0.34	-0.44	-0.58	-5.01
26	-1.24	-1.16	-0.97	-0.42	-0.34	-0.45	-0.59	-5.17
28	-1.28	-1.20	-1.00	-0.45	-0.32	-0.47	-0.60	-5.33
30	-1.32	-1.23	-1.04	-0.46	-0.30	-0.49	-0.61	-5.46
32	-1.36	-1.27	-1.09	-0.46	-0.27	-0.50	-0.62	-5.57